

# 5V RS232 Transceiver with Advanced Power Management and One Receiver Active in SHUTDOWN

## FEATURES

- One Receiver Remains Active While in SHUTDOWN
- ESD Protection over  $\pm 10\text{kV}$
- Uses Small Capacitors:  $0.1\mu\text{F}$ ,  $0.2\mu\text{F}$ ,  $1.0\mu\text{F}$
- $60\mu\text{A}$  Supply Current in SHUTDOWN
- Pin-Compatible with LT1137A
- 120kBaud Operation for  $R_L = 3\text{k}$ ,  $C_L = 2500\text{pF}$
- 250kBaud Operation for  $R_L = 3\text{k}$ ,  $C_L = 1000\text{pF}$
- CMOS Comparable Low Power 30mW
- Operates from a Single 5V Supply
- Easy PC Layout – Flowthrough Architecture
- Rugged Bipolar Design
- Outputs Assume a High Impedance State When Off or Powered Down
- Absolutely No Latchup
- Available in SO and SSOP Packages

## APPLICATIONS

- Notebook Computers
- Palmtop Computers

## DESCRIPTION


The LT1237 is an advanced low power three driver, five receiver RS232 transceiver. Included on the chip is a shutdown pin for reducing supply current near zero. During SHUTDOWN one receiver remains active to detect incoming RS232 signals, for example, to wake up a system.

The LT1237 is fully compliant with all EIA RS232 specifications. New ESD structures on the chip allow the LT1237 to survive multiple  $\pm 10\text{kV}$  strikes, eliminating the need for costly TransZorbs® on the RS232 line pins.


The LT1237 operates in excess of 120k baud even driving heavy capacitive loads. Two SHUTDOWN modes allow the driver outputs to be shut down separately from the receivers for more versatile control of the RS232 interface. During SHUTDOWN, drivers and receivers assume a high impedance state.

TransZorb is a registered trademark of General Instruments, GSI

## TYPICAL APPLICATION



## Output Waveforms



1237 TA02

LT1237 TA01

## ABSOLUTE MAXIMUM RATINGS

(Note 1)

Supply Voltage ( $V_{CC}$ )	6V
$V^+$	13.2V
$V^-$	-13.2V
Input Voltage	
Driver	$V^-$ to $V^+$
Receiver	-30V to 30V
Output Voltage	
Driver	-30V to 30V
Receiver	-0.3V to $V_{CC} + 0.3V$
Short Circuit Duration	
$V^+$	30 sec
$V^-$	30 sec
Driver Output	Indefinite
Receiver Output	Indefinite
Operating Temperature Range	
LT1237I	-40°C to 85°C
LT1237C	0°C to 70°C
Storage Temperature Range	-65°C to 150°C
Lead Temperature (Soldering, 10 sec)	300°C

## PACKAGE/ORDER INFORMATION

TOP VIEW		ORDER PART NUMBER
		LT1237IJ LT1237IN LT1237CJ LT1237CN LT1237CS LT1237CG
J PACKAGE 28-LEAD CERAMIC DIP	N PACKAGE 28-LEAD PLASTIC DIP	
S PACKAGE 28-LEAD SOL	G PACKAGE 28-LEAD SSOP	
$T_{JMAX} = 150^{\circ}\text{C}, \theta_{JA} = 62^{\circ}\text{C/W (J)}$ $T_{JMAX} = 150^{\circ}\text{C}, \theta_{JA} = 56^{\circ}\text{C/W (N)}$ $T_{JMAX} = 150^{\circ}\text{C}, \theta_{JA} = 85^{\circ}\text{C/W (S)}$ $T_{JMAX} = 150^{\circ}\text{C}, \theta_{JA} = 96^{\circ}\text{C/W (G)}$		

Consult factory for Military grade parts.

## ELECTRICAL CHARACTERISTICS (Note 2)

PARAMETER	CONDITIONS	MIN	TYP	MAX	UNITS
<b>Power Supply Generator</b>					
$V^+$ Output			7.9		V
$V^-$ Output			-7		V
Supply Current ( $V_{CC}$ )	$T_A = 25^{\circ}\text{C}$ (Note 3)		6	12	mA
		●	6	14	mA
Supply Current when OFF ( $V_{CC}$ )	SHUTDOWN (Note 4) DRIVER DISABLE	●	0.06	0.15	mA
		●	3.00		mA
Supply Rise Time SHUTDOWN to Turn-On	$C1 = C2 = 0.2\mu\text{F}$ , $C^+ = 1.0\mu\text{F}$ , $C^- = 0.1\mu\text{F}$		2		ms
ON/OFF Pin Thresholds	Input Low Level (Device SHUTDOWN)	●	0.8	1.2	V
	Input High Level (Device Enabled)	●	1.6	2.4	V
ON/OFF Pin Current	$0V \leq V_{ON/OFF} \leq 5V$	●	-15	80	$\mu\text{A}$
Driver Disable Pin Thresholds	Input Low Level (Drivers Enabled)	●	0.8	1.4	V
	Input High Level (Drivers Disabled)	●	1.4	2.4	V
Driver Disable Pin Current	$0V \leq V_{DRIVER\ DISABLE} \leq 5V$	●	-10	500	$\mu\text{A}$
Oscillator Frequency	Driver Outputs Loaded $R_L = 3k$		130		kHz

## ELECTRICAL CHARACTERISTICS (Note 2)

PARAMETER	CONDITIONS			MIN	TYP	MAX	UNITS
Any Driver							
Output Voltage Swing	Load = 3k to GND	Positive Negative	● ●	5.0	7.5 −6.3	−5.0	V V
Logic Input Voltage Level	Input Low Level (V <sub>OUT</sub> = High) Input High Level (V <sub>OUT</sub> = Low)	● ●	2.0	1.4 1.4	0.8		V V
Logic Input Current	0.8V ≤ V <sub>IN</sub> ≤ 2V	●		5	20		μA
Output Short-Circuit Current	V <sub>OUT</sub> = 0V		±9	17			mA
Output Leakage Current	SHUTDOWN V <sub>OUT</sub> = ±30V (Note 4)	●		10	100		μA
Data Rate	R <sub>L</sub> = 3k, C <sub>L</sub> = 2500pF R <sub>L</sub> = 3k, C <sub>L</sub> = 1000pF		120 250				kBaud kBaud
Slew Rate	R <sub>L</sub> = 3k, C <sub>L</sub> = 51pF R <sub>L</sub> = 3k, C <sub>L</sub> = 2500pF			15 4	30 7		V/μs V/μs
Propagation Delay	Output Transition t <sub>HL</sub> High to Low (Note 5) Output Transition t <sub>LH</sub> Low to High				0.6 0.5	1.3 1.3	μs μs
Any Receiver							
Input Voltage Thresholds	Input Low Threshold (V <sub>OUT</sub> = High) Input High Threshold (V <sub>OUT</sub> = Low)		0.8	1.3 1.7			V V
Hysteresis		●	0.1	0.4	1.0		V
Input Resistance	V <sub>IN</sub> = ±10V		3	5	7		kΩ
Output Leakage Current	SHUTDOWN (Note 4) 0 ≤ V <sub>OUT</sub> ≤ V <sub>CC</sub>	●		1	10		μA
Receivers 1, 2, 3, 4							
Output Voltage	Output Low, I <sub>OUT</sub> = −1.6mA Output High, I <sub>OUT</sub> = 160μA (V <sub>CC</sub> = 5V)	● ●		0.2 3.5	0.4		V V
Output Short-Circuit Current	Sinking Current, V <sub>OUT</sub> = V <sub>CC</sub> Sourcing Current, V <sub>OUT</sub> = 0V		−10 10	−20 20			mA mA
Propagation Delay	Output Transition t <sub>HL</sub> High to Low (Note 6) Output Transition t <sub>LH</sub> Low to High			250 350	600 600		ns ns
Receiver 5 (LOW I <sub>SUPPLY RX</sub> )							
Output Voltage	Output Low, I <sub>OUT</sub> = −500μA Output High, I <sub>OUT</sub> = 160μA (V <sub>CC</sub> = 5V)	● ●		0.2 3.5	0.4		V V
Output Short-Circuit Current	Sinking Current, V <sub>OUT</sub> = V <sub>CC</sub> Sourcing Current, V <sub>OUT</sub> = 0V		−2 2	−4 4			mA mA
Propagation Delay	Output Transition t <sub>HL</sub> High to Low (Note 6) Output Transition t <sub>LH</sub> Low to High			1.0 0.6	3 3		μs μs

The ● denotes specifications which apply over the operating temperature range ( $0^\circ\text{C} \leq T_A \leq 70^\circ\text{C}$  for commercial grade, and  $-40^\circ\text{C} \leq T_A \leq 85^\circ\text{C}$  for industrial grade).

**Note 1:** Absolute Maximum Ratings are those values beyond which the life of the device may be impaired.

**Note 2:** Testing done at  $V_{CC} = 5V$  and  $V_{ON/OFF} = 3V$ , unless otherwise specified.










**Note 3:** Supply current is measured as the average over several charge pump burst cycles.  $C^+ = 1.0\mu\text{F}$ ,  $C^- = 0.1\mu\text{F}$ ,  $C1 = C2 = 0.2\mu\text{F}$ . All outputs are open, with all driver inputs tied high.

**Note 4:** Measurements in SHUTDOWN are performed with  $V_{ON/OFF} \leq 0.1V$ . Supply current measurements using DRIVER DISABLE are performed with  $V_{DRIVER\ DISABLE} \geq 3V$ .


**Note 5:** For driver delay measurements,  $R_L = 3k$  and  $C_L = 51pF$ . Trigger points are set between the driver's input logic threshold and the output transition to the zero crossing ( $t_{HL} = 1.4V$  to  $0V$  and  $t_{LH} = 1.4V$  to  $0V$ ).

**Note 6:** For receiver delay measurements,  $C_L = 51pF$ . Trigger points are set between the receiver's input logic threshold and the output transition to standard TTL/CMOS logic threshold ( $t_{HL} = 1.3V$  to  $2.4V$  and  $t_{LH} = 1.7V$  to  $0.8V$ ).


# TYPICAL PERFORMANCE CHARACTERISTICS




## TYPICAL PERFORMANCE CHARACTERISTICS




1237 G10



1237 G11



1237 G12



1237 G13

## PIN FUNCTIONS

**V<sub>CC</sub>**: 5V Input Supply Pin. This pin should be decoupled with a 0.1μF ceramic capacitor close to the package pin. Insufficient supply bypassing can result in low output drive levels and erratic charge pump operation.

**GND**: Ground Pin.

**ON/OFF**: TTL/CMOS Compatible Operating Mode Control. A logic low puts the device in the low power SHUTDOWN mode. All three drivers and four receivers (RX1, RX2, RX3, and RX4) assume a high impedance output state in SHUTDOWN. Only receiver RX5 remains active while the transceiver is in SHUTDOWN. The transceiver consumes only 60μA of supply current while in SHUTDOWN. A logic high fully enables the transceiver.

**DRIVER DISABLE**: This pin provides an alternate control for the charge pump and RS232 drivers. A logic high on this pin shuts down the charge pump and places all driver outputs in a high impedance state. All five receivers remain active under these conditions. Floating the driver disable pin or driving it to a logic low level fully enables the transceiver. A logic low on the On/Off pin supersedes the state of the Driver Disable pin. Supply current drops to 3mA when in DRIVER DISABLE mode.

**V<sup>+</sup>**: Positive Supply Output (RS232 Drivers).  $V^+ \approx 2V_{CC} - 1.5\text{V}$ . This pin requires an external charge storage capacitor  $C \geq 1.0\mu\text{F}$ , tied to ground or  $V_{CC}$ . Larger value capacitors may be used to reduce supply ripple. The ratio of the capacitors on  $V^+$  and  $V^-$  should be greater than 5 to 1.

## PIN FUNCTIONS

**V<sup>-</sup>:** Negative Supply Output (RS232 Drivers).  $V^- \approx -(2V_{CC} - 2.5V)$ . This pin requires an external charge storage capacitor  $C \geq 0.1\mu F$ . See the Applications Information section for guidance in choosing filter capacitors for  $V^+$  and  $V^-$ .

**C1<sup>+</sup>, C1<sup>-</sup>, C2<sup>+</sup>, C2<sup>-</sup>:** Commutating Capacitor Inputs, require two external capacitors  $C \geq 0.2\mu F$ : one from C1<sup>+</sup> to C1<sup>-</sup>, and another from C2<sup>+</sup> to C2<sup>-</sup>. The capacitor's effective series resistance should be less than  $2\Omega$ . For  $C \geq 1\mu F$ , low ESR tantalum capacitors work well in this application, although small value ceramic capacitors may be used with a minimal reduction in charge pump compliance.

**DRIVER IN:** RS232 Driver Input Pins. These inputs are TTL/CMOS compatible. Inputs should not be allowed to float. Tie unused inputs to  $V_{CC}$ .

**DRIVER OUT:** Driver Outputs at RS232 Voltage Levels. Driver output swing meets RS232 levels for loads up to 3k. Slew rates are controlled for lightly loaded lines. Output current capability is sufficient for load conditions up to 2500pF. Outputs are in a high impedance state when in SHUTDOWN mode,  $V_{CC} = 0V$ , or when the driver disable pin is active. Outputs are fully short-circuit protected from  $V^- + 30V$  to  $V^+ - 30V$ . Applying higher voltages will not damage the device if the overdrive is moderately current limited. Short circuits on one output can load the power

supply generator and may disrupt the signal levels of the other outputs. The driver outputs are protected against ESD to  $\pm 10kV$  for human body model discharges.

**RX IN:** Receiver Inputs. These pins accept RS232 level signals ( $\pm 30V$ ) into a protected 5k terminating resistor. The receiver inputs are protected against ESD to  $\pm 10kV$  for human body model discharges. Each receiver provides 0.4V of hysteresis for noise immunity. Open receiver inputs assume a logic low state.


**RX OUT:** Receiver Outputs with TTL/CMOS Voltage Levels. Outputs RX1, RX2, RX3, and RX4 are in a high impedance state when in SHUTDOWN mode to allow data line sharing. Outputs, including LOW-Q RX OUT, are fully short-circuit protected to ground or  $V_{CC}$  with the power on, off, or in SHUTDOWN mode.

**LOW Q-CURRENT RX IN:** Low Power Receiver Input. This special receiver remains active when the part is in SHUTDOWN mode, consuming typically 60 $\mu A$ . This receiver has the same 5k input impedance and  $\pm 10kV$  ESD protection characteristics as the other receivers.

**LOW Q-CURRENT RX OUT:** Low Power Receiver Output. This pin produces the same TTL/CMOS output voltage levels as receivers RX1, RX2, RX3, and RX4 with slightly decreased speed and short-circuit current. Data rates to 120k baud are supported by this receiver.

## ESD PROTECTION

The RS232 line inputs of the LT1237 have on-chip protection from ESD transients up to  $\pm 10kV$ . The protection structures act to divert the static discharge safely to system ground. In order for the ESD protection to function effectively, the power supply and ground pins of the LT1237 must be connected to ground through low impedances. The power supply decoupling capacitors and charge pump storage capacitors provide this low impedance in normal application of the circuit. The only constraint is that low ESR capacitors must be used for bypassing and charge storage. ESD testing must be done with pins  $V_{CC}$ ,  $V_L$ ,  $V^+$ ,  $V^-$ , and GND shorted to ground or connected with low ESR capacitors.



The V<sup>-</sup> filter capacitor should be selected to obtain low ripple when the drivers are loaded, forcing the charge pump into continuous mode. A minimum value 0.1μF is suggested.


If more than one line must be monitored, the DRIVER DISABLE mode provides a power efficient operating option. The DRIVER DISABLE mode turns off the charge pump and RS232 drivers, but keeps all five receivers active. Power consumption in DRIVER DISABLE mode is 3mA from  $V_{CC}$ .

1237 TA03


# PACKAGE DESCRIPTION

Dimensions in inches (millimeters) unless otherwise noted.


## J Package 28-Lead Ceramic DIP



## N Package 28-Lead Plastic DIP



## S Package 28-Lead SOL



NOTE:  
PIN 1 IDENT, NOTCH ON TOP AND CAVITIES ON THE BOTTOM OF PACKAGES ARE THE MANUFACTURING OPTIONS.  
THE PART MAY BE SUPPLIED WITH OR WITHOUT ANY OF THE OPTIONS.

## G Package 28-Lead SSOP

