

*TMS320 DSP
DESIGNER'S NOTEBOOK*

Switching From Bootloader to MP Mode with TMS320C31

APPLICATION BRIEF: SPRA219

*Daniel Chen
Digital Signal Processing Products
Semiconductor Group*

*Texas Instruments
March 1993*



IMPORTANT NOTICE

Texas Instruments (TI) reserves the right to make changes to its products or to discontinue any semiconductor product or service without notice, and advises its customers to obtain the latest version of relevant information to verify, before placing orders, that the information being relied on is current.

TI warrants performance of its semiconductor products and related software to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are utilized to the extent TI deems necessary to support this warranty. Specific testing of all parameters of each device is not necessarily performed, except those mandated by government requirements.

Certain application using semiconductor products may involve potential risks of death, personal injury, or severe property or environmental damage ("Critical Applications").

TI SEMICONDUCTOR PRODUCTS ARE NOT DESIGNED, INTENDED, AUTHORIZED, OR WARRANTED TO BE SUITABLE FOR USE IN LIFE-SUPPORT APPLICATIONS, DEVICES OR SYSTEMS OR OTHER CRITICAL APPLICATIONS.

Inclusion of TI products in such applications is understood to be fully at the risk of the customer. Use of TI products in such applications requires the written approval of an appropriate TI officer. Questions concerning potential risk applications should be directed to TI through a local SC sales office.

In order to minimize risks associated with the customer's applications, adequate design and operating safeguards should be provided by the customer to minimize inherent or procedural hazards.

TI assumes no liability for applications assistance, customer product design, software performance, or infringement of patents or services described herein. Nor does TI warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right of TI covering or relating to any combination, machine, or process in which such semiconductor products or services might be or are used.

TRADEMARKS

TI is a trademark of Texas Instruments Incorporated.

Other brands and names are the property of their respective owners.

CONTACT INFORMATION

US TMS320 HOTLINE	(281) 274-2320
US TMS320 FAX	(281) 274-2324
US TMS320 BBS	(281) 274-2323
US TMS320 email	dsph@ti.com

Contents

Abstract7

Design Problem.....8

Solution8

Switching From Bootloader to MP Mode with TMS320C31

Abstract

The 'C31 bootloader is expected to be used only at reset and then the 'C31 will stay in MCBL mode the rest of the time. It is sometimes convenient that once loading is done, the MCBL/MP pin is changed to enable the microprocessor memory map. This document discusses a technique to change from bootloader mode to microprocessor mode “on-the-fly”.



Design Problem

How can I boot change from bootloader mode to microprocessor mode “on-the-fly?”

Solution

The 'C31 bootloader is expected to be used at reset and then the 'C31 stays in MCBL mode the rest of the time. Yet, it is sometimes convenient that once loading is done, change the MCBL/MP pin to enable the microprocessor memory map.

The 'C31 device will continue to sample the MCBL/MP pin status. Therefore, it is possible to change the MCBL/MP mode without resetting the device. The user needs to make sure the MCBL/MP pin is high during the bootloading and the 'C31 is not using the overlapping memory during the mode transition time.

The user should use a routine in which it is guaranteed that no program fetch or data read/write is performed to the overlapping memory during the transition time. A 'C31-initiated interrupt issued via an otherwise unused pin (e.g., XF0, a timer bit-I/O) can be used to request a transition on the MCBL pin.