

Configuring Digital I/Os of the TMS320F240 DSP Controller

APPLICATION REPORT: SPRA443

Mohammed S. Arefeen and Jeff Stafford

*Digital Signal Processing Solutions
April 1998*



IMPORTANT NOTICE

Texas Instruments (TI) reserves the right to make changes to its products or to discontinue any semiconductor product or service without notice, and advises its customers to obtain the latest version of relevant information to verify, before placing orders, that the information being relied on is current.

TI warrants performance of its semiconductor products and related software to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are utilized to the extent TI deems necessary to support this warranty. Specific testing of all parameters of each device is not necessarily performed, except those mandated by government requirements.

Certain application using semiconductor products may involve potential risks of death, personal injury, or severe property or environmental damage ("Critical Applications").

TI SEMICONDUCTOR PRODUCTS ARE NOT DESIGNED, INTENDED, AUTHORIZED, OR WARRANTED TO BE SUITABLE FOR USE IN LIFE-SUPPORT APPLICATIONS, DEVICES OR SYSTEMS OR OTHER CRITICAL APPLICATIONS.

Inclusion of TI products in such applications is understood to be fully at the risk of the customer. Use of TI products in such applications requires the written approval of an appropriate TI officer. Questions concerning potential risk applications should be directed to TI through a local SC sales office.

In order to minimize risks associated with the customer's applications, adequate design and operating safeguards should be provided by the customer to minimize inherent or procedural hazards.

TI assumes no liability for applications assistance, customer product design, software performance, or infringement of patents or services described herein. Nor does TI warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right of TI covering or relating to any combination, machine, or process in which such semiconductor products or services might be or are used.

TRADEMARKS

TI is a trademark of Texas Instruments Incorporated.

Other brands and names are the property of their respective owners.

CONTACT INFORMATION

US TMS320 HOTLINE	(281) 274-2320
US TMS320 FAX	(281) 274-2324
US TMS320 BBS	(281) 274-2323
US TMS320 email	dsph@ti.com

Contents

Abstract	7
Product Support.....	8
World Wide Web	8
Email.....	8
Design Problem.....	9
Solution.....	9

Tables

Table 1. Registers Used for GPIO Configuration	9
Table 2. Configuration Details for Each Shared I/O Pin	10

Examples

Example 1. Code to Configure I/O that Uses the OCR and PxDATDIR Registers.....	10
Example 2. Code to Configure I/O Using Individual Peripheral Control Registers	11
Example 3. Code to Configure Pin 64 as an Input	11

Configuring Digital I/Os of the TMS320F240 DSP Controller

Abstract

This document describes how to configure the digital I/Os of the Texas Instruments (TI™) TMS320F240. The TMS320F240 DSP controller has 28 digital I/O pins. All 28 digital I/Os are multiplexed with other functions. These I/Os are in addition to the 64k of addressable I/O space associated with the address and data pins. Since the I/O pins are shared with functions from several different peripheral modules, the user must be aware of several configuration registers described in this document.



Product Support

World Wide Web

Our World Wide Web site at www.ti.com contains the most up to date product information, revisions, and additions. Users registering with TI&ME can build custom information pages and receive new product updates automatically via email.

Email

For technical issues or clarification on switching products, please send a detailed email to dsph@ti.com. Questions receive prompt attention and are usually answered within one business day.



Design Problem

How do I configure the digital I/Os of the TMS320F240?

Solution

The Texas Instruments (TI™) TMS320F240 DSP controller has 28 digital I/O pins. All 28 digital I/Os are multiplexed with other functions. These I/Os are in addition to the 64k of addressable I/O space associated with the address and data pins. Since the I/O pins are shared with functions from several different peripheral modules, the user must be aware of several configuration registers. Table 1 shows the configuration registers that are used for the GPIO.

Table 1. Registers Used for GPIO Configuration

Register	Address	Name	Affected Pins
SCIPC2	705Eh	SCI Port Control Reg 2	43-4
SPIPC1	7040h	SPI Port Control Reg 1	45, 48
SPIPC2	704Eh	SPI Port Control Reg 2	49, 51
XINT2CR	7078h	Ext Int 2 Control Reg	54
XINT3CR	707Ah	Ext Int 3 Control Reg	55
OCRA	7090h	I/O Mux Control Reg A	72-3, 90-1, 100-2, 105-9
OCRB	7092h	I/O Mux Control Reg B	65-70
PADATDIR	7098h	I/O Port A Data/Dir Reg	72-3, 90-1
PBDATDIR	709Ah	I/O Port B Data/Dir Reg	100-2, 105-9
PCDATDIR	709Ch	I/O Port B Data/Dir Reg	63-70

Configuration details for each pin are listed in Table 2. Note that Pin 64 is a useful pin for debugging purposes. In addition to the CPUCLK, the WDCLK and the SYSCLK can be output from this pin. Also, the XINT2 and XINT3 pins are configured as GPIO when these interrupts are disabled. The user should be careful not to inadvertently drive these outputs by configuring these pins as inputs.

Table 2. Configuration Details for Each Shared I/O Pin

Pin #	Shared Function	After RESET	Make Pin GPIO	Configure as Input	Read Data from	Configure as Output	Write Data to
43	SCIRXD	GPI	SCIPC2.1=0	SCIPC2.0=0	SCIPC2.3	SCIPC2.0=1	SCIPC2.2
44	SCITXD	GPI	SCIPC2.5=0	SCIPC2.4=0	SCIPC2.7	SCIPC2.4=1	SCIPC2.6
45	SPISIMO	GPI	SPIPC2.5=0	SPIPC2.4=0	SPIPC2.7	SPIPC2.4=1	SPIPC2.6
48	SPISOMI	GPI	SPIPC2.1=0	SPIPC2.0=0	SPIPC2.3	SPIPC2.0=0	SPIPC2.2
49	SPICLK	GPI	SPIPC1.1=0	SPIPC1.0=0	SPIPC1.3	SPIPC1.0=0	SPIPC1.2
51	SPISTE ¹	GPI	SPIPC1.5=0	SPIPC1.4=0	SPIPC1.7	SPIPC1.4=1	SPIPC1.6
54	XINT2	GPI	XINT2CR.0=0	XINT2CR.4=0	XINT2CR.6	XINT2CR.4=1	XINT2CR.3
55	XINT3	GPI	XINT3CR.0=0	XINT3CR.4=0	XINT3CR.6	XINT3CR.4=1	XINT3CR.3
63	ADC SOC	GPI	OCRB.0=0	PCDATDIR.8=0	PCDATDIR.0	PCDATDIR.8=1	PCDATDIR.0
64	CPUCLK	CPUCLK	SYSCR.6,7=00	PCDATDIR.9=0	PCDATDIR.1	PCDATDIR.9=1	PCDATDIR.1
65	XF	GPO-low	OCRB.2=1	PCDATDIR.10=0	PCDATDIR.2	PCDATDIR.10=1	PCDATDIR.1
66	BIO	GPO-low	OCRB.3=1	PCDATDIR.11=0	PCDATDIR.3	PCDATDIR.11=1	PCDATDIR.3
67	CAP1/QEP1	GPI	OCRB.4=0	PCDATDIR.12=0	PCDATDIR.4	PCDATDIR.12=1	PCDATDIR.4
68	CAP2/QEP2	GPI	OCRB.5=0	PCDATDIR.13=0	PCDATDIR.5	PCDATDIR.13=1	PCDATDIR.5
69	CAP3	GPI	OCRB.6=0	PCDATDIR.14=0	PCDATDIR.6	PCDATDIR.14=1	PCDATDIR.6
70	CAP4	GPI	OCRB.7=0	PCDATDIR.15=0	PCDATDIR.7	PCDATDIR.15=1	PCDATDIR.7
72	ADCIN0	GPI	OCRA.0=0	PADATDIR.8=0	PADATDIR.0	PADATDIR.8=1	PADATDIR.0
73	ADCIN1	GPI	OCRA.1=0	PADATDIR.9=0	PADATDIR.1	PADATDIR.9=1	PADATDIR.1
90	ADCIN9	GPI	OCRA.2=0	PADATDIR.10=0	PADATDIR.2	PADATDIR.10=1	PADATDIR.2
91	ADCIN8	GPI	OCRA.3=0	PADATDIR.11=0	PADATDIR.3	PADATDIR.11=1	PADATDIR.3
100	PWM7/CMP7	GPI	OCRA.8=0	PBDATDIR.8=0	PBDATDIR.0	PBDATDIR.8=1	PBDATDIR.0
101	PWM8/CMP8	GPI	OCRA.9=0	PBDATDIR.9=0	PBDATDIR.1	PBDATDIR.9=1	PBDATDIR.0
102	PWM9/CMP9	GPI	OCRA.10=0	PBDATDIR.10=0	PBDATDIR.2	PBDATDIR.10=1	PBDATDIR.2
105	T1PWM/T1CMP	GPI	OCRA.11=0	PBDATDIR.11=0	PBDATDIR.3	PBDATDIR.11=1	PBDATDIR.3
106	T2PWM/T2CMP	GPI	OCRA.12=0	PBDATDIR.12=0	PBDATDIR.4	PBDATDIR.12=1	PBDATDIR.4
107	T3PWM/T3CMP	GPI	OCRA.13=0	PBDATDIR.13=0	PBDATDIR.5	PBDATDIR.13=1	PBDATDIR.5
108	TMRDIR	GPI	OCRA.14=0	PBDATDIR.14=0	PBDATDIR.6	PBDATDIR.14=1	PBDATDIR.6
109	TMRCLK	GPI	OCRA.15=0	PBDATDIR.15=0	PBDATDIR.7	PBDATDIR.15=1	PBDATDIR.7

The code in Example 1 shows how to configure the pins connected to OCRA (I/O Mux Control Reg A) as general-purpose inputs (Pins 72-3, 90-1, 100-2, 105-9). After the pins are set as GPIO in the OCRA register, PADATDIR (I/O Port A Data/Dir Reg) and PBDATDIR (I/O Port B Data/Dir Reg) are configured to set the pins as inputs.

Example 1. Code to Configure I/O that Uses the OCR and PxDATDIR Registers

```

OCRA      .set 7090h
PADATDIR  .set 7098h
PBDATDIR  .set 709Ah
LDP       #0E1H      ;Point to appropriate data page,
LACC      #0h        ;pins IOPA0~IOPA3 and IOPB0~IOPB7
SACL      OCRA       ;are configured as I/Os pins.
SACL      PADATDIR   ;IOPA0~IOPA3 are configured as inputs.
LACC      #00F0h     ;Pins IOPB7~IOPB4 are configured as inputs.
SACL      PBDATDIR   ;Pins IOPB3~IOPB0 are configured as outputs.
LACC      PBDATDIR   ;Reading input states IOPB7~IOPB4.
AND       #F000h     ;ACC = input status.

```

¹ SPISTE automatically becomes a GPIO when the SPI is in Master mode.



The code in Example 2 shows how to configure Pin 43 (SCIRXD) as digital input and Pin 44 (SCITXD) as digital output-low. Register SCIPC2 (port control register) needs to be configured to setup Pins 43 and 44.

Example 2. Code to Configure I/O Using Individual Peripheral Control Registers

```
SCIPC2      .set  705Eh
LDP         #0E0h      ;Point to the appropriate data page
SPLK        #0010h, SCIPC2 ;Configure SCITXD as output-low and
LACC        SCIPC2      ;SCIRXD as input.
OR          #040h      ;Set SCITXD as output-high, without
SACL        SCIPC2      ;changing other configuration bits.
```

The Pin 64 (IOPC1) is associated with the System Control Register. Pin 64 can be configured as an I/O by resetting (putting zero) bits 7 and 6 of the System Control Register (SYSCR @ 7018h). Configuring the PCDATDIR register as shown in Example 1 can set the direction and data of Pin 64. The code in Example 3 shows how to configure Pin 64 as a digital input. As previously noted, Pin 64 is a useful pin for debugging and should be reserved for this purpose.

Example 3. Code to Configure Pin 64 as an Input

```
PCDATDIR    .set  709Ch
SYSCR       .set  7018h
LDP         #0E0h
LACC        SYSCR
AND         #0FF3Fh
SACL        SYSCR
LDP         #0E1
LACC        #0h
SACL        PCDATDIR
```