

LT1078 Macromodel

```

*
* Linear Technology LT1078 op amp model (with calls for LT1079, LT1077)
* Written: 10-17-1989 10:20:02 Type: Bipolar pnp input, internal comp.
* Typical specs:
* Vos=4.0E-05, Ib=6.0E-09, Ios=5.0E-11, GBP=2.0E+05Hz, Phase mar.= 60 deg,
* SR(-)=8.0E-02V/us, SR(+)=7.6E-02V/us, Av= 120 dB, CMMR= 108 dB,
* Vsat(+)=1.00V, Vsat(-)=0.00V, Isc=+/-15.0mA, Iq=45uA.
* (input common mode clamp active)
* (3 for 1!)
*
* Connections: + - V+V-0
.subckt LT1078 3 2 7 4 6
* input
rc1 4 80 2.653E+04
rc2 4 90 2.653E+04
q1 80 102 10 qm1
q2 90 103 11 qm2
rb1 2 102 6.000E+02
rb2 3 103 6.000E+02
dcm1 105 102 dm2
dcm2 105 103 dm2
vcmc 105 4 4.000E-01
c1 80 90 8.660E-12
re1 10 12 4.958E+03
re2 11 12 4.958E+03
iee 7 12 2.412E-06
re 12 0 8.292E+07
ce 12 0 1.579E-12
* models
.model qm1 pnp (is=8.000E-16 bf=1.992E+02)
.model qm2 pnp (is=8.012E-16 bf=2.008E+02)
.model dm1 d (is=2.119E-24)
.model dm2 d (is=8.000E-16)
.ends LT1078
*
.subckt LT1079 3 2 7 4 6
x_LT1079 3 2 7 4 6 LT1078
.ends LT1079
*
.subckt LT1077 3 2 7 4 6
x_LT1077 3 2 7 4 6 LT1078
.ends LT1077
*
* - - - - - * fini LT1078 family * - - - - - * [oamm vp01 10/89]
* intermediate
gcm 0 8 12 0 1.501E-10
ga 8 0 80 90 3.770E-05
r2 8 0 1.000E+05
c2 1 8 3.000E-11
gb 1 0 8 0 1.396E+02
* output
ro1 1 110 1.000E+02
ro2a 1 0 1.083E+03
ro2b 6 110 8.170E+02
ec 17 0 110 0 1
d1 1 17 dm1
d2 17 1 dm1
d3 110 13 dm2
d4 14 110 dm2
d5 6 110 dm2
d6 110 6 dm2
vc 7 13 1.790E+00
ve 14 4 7.901E-01
ip 7 4 4.259E-05
dsub 4 7 dm2

```